

MH-M18 Wireless Bluetooth MP3 Audio Receiver board BLT 4.2 mp3 lossless decoder

| | M18 | M28 | M38 |
|------------------------------------|--|-----|-----------|
| MICRO USB (power supply) | × | √ | √ |
| Audio headphone jack | × | √ | × |
| Built-in amplifier | × | × | √ (5W+5W) |
| Lithium battery powered | √ | √ | √ |
| Support USB sound card(free drive) | × | × | √ |
| Volume memory/adjustment | √ | × | × |
| MUTE interface | √ | × | × |
| Button extension | √ | × | × |
| Bluetooth version | Bluetooth V4.2 | | |
| Support Bluetooth protocol | HFPV1.7, A2DPV1.2, AVRCPV1.5, AVCTPV1.2, AVDTPV1.2 | | |
| Format support | WAV/WMA/FLAC/APE/MP3 lossless decoding, stereo dual channel output | | |
| Operating Voltage | 5V/3.7V-4.2V | | |
| Not connected broadcast status | 5.5MA | | |
| Connection work status | 20MA | | |
| Deep sleeping | 3UA | | |
| Transmission distance | 20M (MAX) | | |
| Operating temperature | "-40°C-+85°C | | |
| Sensitivity | "-87dbm | | |

