

# Cascadable Silicon Bipolar MMIC Amplifier

# Technical Data

#### **MSA-0186**

#### **Features**

- Cascadable 50  $\Omega$  Gain Block
- 3 dB Bandwidth: DC to 0.9 GHz
- **High Gain:** 17.5 dB Typical at 0.5 GHz
- Unconditionally Stable (k>1)
- Surface Mount Plastic Package
- Tape-and-Reel Packaging Option Available<sup>[1]</sup>

#### Note:

 Refer to PACKAGING section "Tapeand-Reel Packaging for Semiconductor Devices".

## **Description**

The MSA-0186 is a high performance silicon bipolar Monolithic Microwave Integrated Circuit (MMIC) housed in a low cost, surface mount plastic package. This MMIC is designed for use as a general purpose  $50~\Omega$  gain block. Typical applications include narrow and broad band IF and RF amplifiers in commercial and industrial applications.


The MSA-series is fabricated using HP's  $10\,\mathrm{GHz}\,f_T, 25\,\mathrm{GHz}\,f_{MAX},$  silicon bipolar MMIC process which uses nitride self-alignment,

## 86 Plastic Package



ion implantation, and gold metallization to achieve excellent performance, uniformity and reliability. The use of an external bias resistor for temperature and current stability also allows bias flexibility.

## **Typical Biasing Configuration**



5965-9694E 6-262

MSA-0186 Absolute Maximum Ratings

Parameter	Absolute Maximum <sup>[1]</sup>				
Device Current	40 mA				
Power Dissipation <sup>[2,3]</sup>	200 mW				
RF Input Power	+13dBm				
Junction Temperature	150°C				
Storage Temperature	-65 to 150°C				

Thermal Resistance $[2,4]$ :					
$\theta_{\rm jc} = 115$ °C/W					

#### **Notes:**

- 1. Permanent damage may occur if any of these limits are exceeded.
- 2.  $T_{CASE} = 25$ °C.
- 3. Derate at 8.7 mW/°C for  $T_C > 127$ °C.
- 4. See MEASUREMENTS section "Thermal Resistance" for more information.

# Electrical Specifications<sup>[1]</sup>, $T_A = 25$ °C

Symbol	Parameters and Test Conditions: l	Units	Min.	Тур.	Max.	
GP	Power Gain $( S_{21} ^2)$	f = 0.1 GHz f = 0.5 GHz	dB	15.5	18.5 17.5	
$\Delta G_{ m P}$	Gain Flatness	f = 0.1  to  0.6  GHz	dB		± 0.7	
f <sub>3 dB</sub>	3 dB Bandwidth		GHz		0.9	
VSWR	Input VSWR	f = 0.1  to  3.0  GHz			1.3:1	
	Output VSWR	f = 0.1  to  3.0  GHz			1.2:1	
NF	$50~\Omega$ Noise Figure	f = 0.5  GHz	dB		5.5	
P <sub>1 dB</sub>	Output Power at 1 dB Gain Compression	f = 0.5  GHz	dBm		1.5	
IP <sub>3</sub>	Third Order Intercept Point	f = 0.5  GHz	dBm		14.0	
$t_{\mathrm{D}}$	Group Delay	f = 0.5  GHz	psec		200	
$V_{d}$	Device Voltage		V	4.0	5.0	6.0
dV/dT	Device Voltage Temperature Coefficient		mV/°C		-9.0	

#### Note:

## **Part Number Ordering Information**

Part Number	No. of Devices	Container		
MSA-0186-BLK	100	Antistatic Bag		
MSA-0186-TR1	1000	7" Reel		

For more information refer to PACKAGING section, "Tape and Reel Packaging for Semiconductor Devices."

<sup>1.</sup> The recommended operating current range for this device is 13 to 25 mA. Typical performance as a function of current is on the following page.

MSA-0186 Typical Scattering Parameters (Z  $_{0}$  = 50  $\Omega,$   $T_{_{A}}$  = 25  $^{\circ}\!C,$   $I_{_{d}}$  = 17 mA)

Freq.	$\mathbf{S}_{11}$		$\mathbf{S}_{21}$		$\mathbf{S_{12}}$			$\mathbf{S}_{22}$		
GHz	Mag	Ang	dB	Mag	Ang	dB	Mag	Ang	Mag	Ang
0.1	.05	148	18.5	8.39	171	-23.0	.071	4	.08	<b>-</b> 7
0.2	.06	124	18.3	8.22	162	-22.8	.073	9	.08	-14
0.3	.07	103	18.1	8.03	154	-22.6	.074	13	.07	-24
0.4	.08	89	17.7	7.67	146	-22.2	.078	14	.07	-31
0.5	.08	76	17.4	7.42	139	-21.9	.081	17	.06	-39
0.6	.09	66	17.0	7.06	131	-21.4	.085	21	.06	<b>-4</b> 7
0.8	.10	50	16.2	6.47	119	-20.5	.094	25	.07	<b>–</b> 67
1.0	.10	35	15.3	5.83	107	-19.6	.105	29	.07	-89
1.5	.07	12	13.2	4.57	83	-17.7	.131	30	.08	-165
2.0	.02	<b>-1</b> 2	11.3	3.67	64	-16.1	.157	27	.08	156
2.5	.06	165	9.8	3.09	50	-14.8	.182	24	.08	134
3.0	.14	150	8.3	2.60	34	-13.9	.202	19	.09	124
3.5	.23	137	7.0	2.24	20	-13.4	.213	12	.09	117
4.0	.31	125	5.7	1.93	6	-13.0	.223	5	.09	114
5.0	.45	105	3.3	1.46	-17	-12.7	.231	<b>-</b> 5	.09	132

A model for this device is available in the DEVICE MODELS section.

# Typical Performance, $T_A = 25^{\circ}C$

(unless otherwise noted)




Figure 1. Typical Power Gain vs. Frequency,  $T_A=25^{\circ}C,\,I_d=17$  mA.




Figure 2. Device Current vs. Voltage.




Figure 3. Output Power at 1 dB Gain Compression, NF and Power Gain vs. CaseTemperature,  $f=0.5~\mathrm{GHz},$   $I_d=17~\mathrm{mA}.$ 




Figure 4. Output Power at 1 dB Gain Compression vs. Frequency.





Figure 5. Noise Figure vs. Frequency.

## **86 Plastic Package Dimensions**



**DIMENSIONS ARE IN MILLIMETERS (INCHES)**