

## Product Description

5A 75W DC-DC Adjustable Step-down Module Step Down Modules with Voltmeter

Performance parameters:

Input voltage range:4-38VDC(Note:input voltage not exceeding 38V)

Output voltage range:1.25-36VDC adjustable

Output current: 0-5A

Output power: 75W

voltmeter range: 4 to 40V, error  $\pm 0.1V$

Operating frequency: 180KHz

High efficiency up to 96 percent

Built in thermal shutdown function

Built in current limit function

Built in output short protection function

Input reverse polarity protection: None (if required, high current diode in series with the input).

L x W x H =6.6x3.9x1.8CM

Weight: 28g

